

## BLS WIRE LIST

July 15, 2002

CABLE DESCRIPTION	END #1	END #2	WIRE SIZE/TYPE	WIRE LENGTH
1000 INPUT LINE to CIRCUIT BREAKER	HUBBEL TWIST LOCK GND-GREEN	GREEN-GROUND 1/4" RING TONGUE	12 GA12/5 SO CORD"	84"
1000 INPUT LINE to CIRCUIT BREAKER	HUBBEL TWIST LOCK NEUT-WHITE	NEUTRAL WHITE SPADE LUG 0.250	12/5 SO CORD"	84"
1000 INPUT LINE to CIRCUIT BREAKER	HUBBEL TWIST LOCK X-BLACK	PHASE-A BLK #10 RNG TNG	12/5 SO CORD"	84"
1000 INPUT LINE to CIRCUIT BREAKER	HUBBEL TWIST LOCK Y-RED	PHASE-B RED #10 RNG TNG	12/5 SO CORD"	84"
1000 INPUT LINE to CIRCUIT BREAKER	HUBBEL TWIST LOCK Z-ORANGE	PHASE-C ORG #10 RNG TNG	12/5 SO CORD"	84"
1001 PHASE-A CIRCUIT BREAKER to SSR	#10 RING TONGUE	#8 RING TONGUE	14 GA BLACK	12"
1002 PHASE-B CIRCUIT BREAKER to SSR	#10 RING TONGUE	#8 RING TONGUE	14 GA RED	13"
1003 PHASE-C CIRCUIT BREAKER to SSR	#10 RING TONGUE	#8 RING TONGUE	14 GA ORANGE	15"
1004 PHASE-A CIRCUIT BRKR to XFRMR BRD.	#10 RING TONGUE	SPADE LUG 0.250"	14 GA BLACK	9"
1005 PHASE-B CIRCUIT BRKR to XFRMR BRD.	#10 RING TONGUE	SPADE LUG 0.250"	14 GA RED	10"
1006 PHASE-C CIRCUIT BRKR to XFRMR BRD.	#10 RING TONGUE	SPADE LUG 0.250"	14 GA ORANGE	8.5"
1007 PHASE-A SSR to SS RESISTOR	#8 RING TONGUE	SOLDER TINNED	14 GA BLACK	7.5"
1008 PHASE-B SSR to SS RESISTOR	#8 RING TONGUE	SOLDER TINNED	14 GA RED	7.5"
1009 PHASE-C SSR to SS RESISTOR	#8 RING TONGUE	SOLDER TINNED	14 GA ORANGE	7.5"
1010 PHASE-A SS RESISTOR to DIR SSR	SOLDER TINNED	#8 RING TONGUE	14 GA BLACK	4"
1011 PHASE-B SS RESISTOR to DIR SSR	SOLDER TINNED	#8 RING TONGUE	14 GA RED	4"
1012 PHASE-C SS RESISTOR to DIR SSR	SOLDER TINNED	#8 RING TONGUE	14 GA ORANGE	4"
1013 BKR1 CIRCUIT BREAKER to LOGIC BRD	SPADE LUG 0.186"	SPADE LUG 0.186"	22 GA RED	27"
1014 BKR2 CIRCUIT BREAKER to LOGIC BRD	SPADE LUG 0.186"	SPADE LUG 0.186"	22 GA ORANGE	27"
1015 RES+3 SSR PIN 3 to CONTROL BRD	#6 RING TONGUE	SPADE LUG 0.186"	22 GA YELLOW	13"
1016 DIR+3 SSR PIN 3 to CONTROL BRD	#6 RING TONGUE	SPADE LUG 0.186"	22 GA BLUE	12"
1017 RLYGND SSR PIN 4 to CONTROL BRD	#6 RING TONGUE	SPADE LUG 0.186"	22 GA GREEN	14"
1018 RES+3 SSR PIN 3 to SSR PIN 3	#6 RING TONGUE	#6 RING TONGUE	22 GA YELLOW	4"
1018 RES+3 SSR PIN 3 to SSR PIN 3	SAME AS END #2 ABOVE	#6 RING TONGUE	22 GA YELLOW	4"
1019 DIR+3 SSR PIN 3 to SSR PIN 3	#6 RING TONGUE	#6 RING TONGUE	22 GA BLUE	4"
1019 DIR+3 SSR PIN 3 to SSR PIN 3	SAME AS END #2 ABOVE	#6 RING TONGUE	22 GA BLUE	4"
1020 RLYGND SSR PIN 4 to SSR PIN 4	#6 RING TONGUE	#6 RING TONGUE	22 GA GREEN	2.5"
1020 RLYGND SSR PIN 4 to SSR PIN 4	SAME AS END #2 ABOVE	#6 RING TONGUE	22 GA GREEN	2.5"
1020 RLYGND SSR PIN 4 to SSR PIN 4	SAME AS END #2 ABOVE	#6 RING TONGUE	22 GA GREEN	2.5"
1020 RLYGND SSR PIN 4 to SSR PIN 4	SAME AS END #2 ABOVE	#6 RING TONGUE	22 GA GREEN	4"
1020 RLYGND SSR PIN 4 to SSR PIN 4	SAME AS END #2 ABOVE	#6 RING TONGUE	22 GA GREEN	2.5"
1021 KT1 THERMAL SWITCH to CONTROL BRD	SPADE LUG 0.250"	SPADE LUG 0.186"	22 GA VIOLET	15"
1022 KT2 THERMAL SWITCH to CONTROL BRD	SPADE LUG 0.250"	SPADE LUG 0.186"	22 GA BLACK	17"
1023 EXTERNAL INTERLOCK FROM BNC INPUT	SOLDER TO ISOLATED BNC	SMB CABLE CONN	RG 188	19"
1024 EX. INTLK JUMPER BNC1 TO BNC 2	SOLDER TO ISOL. BNC 1 SIGNAL	SOLDER TO BNC 2 SIG	22 GA RED	1.5"
1025 EX. INTLK JUMPER BNC1 TO BNC2	SOLDER TO ISOL. BNC 1 GROUND	SOLDER TO BNC 2 GND	22 GA BLACK	1.5"
1026 PRIMARY AC INPUT H1 PHASE A 2-WIRES	#8 RING TONGUE	XFORMER COIL	18 GA BLACK	12"
1027 PRIMARY AC INPUT H2 PHASE B 2-WIRES	#8 RING TONGUE	XFORMER COIL	18 GA BLACK	12"
1028 PRIMARY AC INPUT H3 PHASE C 2-WIRES	#8 RING TONGUE	XFORMER COIL	18 GA BLACK	12"
1029 XFORMER SECONDARY A X1 2-WIRES	1/4" RING TONGUE-X1	#10 RING TONGUE-D001A	10 GA RED	9.5"

**BLS WIRING LIST**

1029	XFORMER SECONDARY A X1 2-WIRES	1/4" RING TONGUE-X1	#10 RING TONGUE-D001A	10 GA RED	8"
1030	XFORMER SECONDARY A X2 2-WIRES	1/4" RING TONGUE-X2	#10 RING TONGUE-D002A	10 GA RED	9.5"
1030	XFORMER SECONDARY A X2 2-WIRES	1/4" RING TONGUE-X2	#10 RING TONGUE-D002A	10 GA RED	8"
1031	XFORMER SECONDARY A X3 2-WIRES	1/4" RING TONGUE-X3	#10 RING TONGUE-D003A	10 GA RED	9.5"
1031	XFORMER SECONDARY A X3 2-WIRES	1/4" RING TONGUE-X3	#10 RING TONGUE-D003A	10 GA RED	8"
1032	XFORMER SECONDARY B X4 2-WIRES	1/4" RING TONGUE-X4	#10 RING TONGUE-D007A	10 GA YELLOW	14"
1032	XFORMER SECONDARY B X4 2-WIRES	1/4" RING TONGUE-X4	#10 RING TONGUE-D007A	10 GA YELLOW	12.5"
1033	XFORMER SECONDARY B X5 2-WIRES	1/4" RING TONGUE-X5	#10 RING TONGUE-D008A	10 GA YELLOW	12.5"
1033	XFORMER SECONDARY B X5 2-WIRES	1/4" RING TONGUE-X6	#10 RING TONGUE-D008A	10 GA YELLOW	11"
1034	XFORMER SECONDARY B X6 2-WIRES	1/4" RING TONGUE-X7	#10 RING TONGUE-D009A	10 GA YELLOW	12"
1034	XFORMER SECONDARY B X6 2-WIRES	1/4" RING TONGUE-X7	#10 RING TONGUE-D009A	10 GA YELLOW	10.5"
1035	XFORMER SECONDARY C X7 2-WIRES	XFORMER COIL	0.250" SPADE LUG	18 GA RED	13"
1036	XFORMER SECONDARY C X8 2-WIRES	XFORMER COIL	0.250" SPADE LUG	18 GA RED	13"
1037	XFORMER SECONDARY C X9 2-WIRES	XFORMER COIL	0.250" SPADE LUG	18 GA RED	13"
1038	XFORMER SECONDARY D X10 2-WIRES	XFORMER COIL	0.250" SPADE LUG	18 GA BLUE	13"
1039	XFORMER SECONDARY D X11 2-WIRES	XFORMER COIL	0.250" SPADE LUG	18 GA BLUE	13"
1040	XFORMER SECONDARY D X12 2-WIRES	XFORMER COIL	0.250" SPADE LUG	18 GA BLUE	13"
1041	XFORMER SECONDARY E X13 2-WIRES	XFORMER COIL	0.250" SPADE LUG	18 GA VIOLET	18"
1042	XFORMER SECONDARY E X14 2-WIRES	XFORMER COIL	0.250" SPADE LUG	18 GA VIOLET	18"
1043	XFORMER SECONDARY E X15 2-WIRES	XFORMER COIL	0.250" SPADE LUG	18 GA VIOLET	18"
1044	XFORMER SECONDARY F X16 2-WIRES	XFORMER COIL	0.250" SPADE LUG	18 GA ORANGE	16"
1045	XFORMER SECONDARY F X17 2-WIRES	XFORMER COIL	0.250" SPADE LUG	18 GA ORANGE	16"
1046	XFORMER SECONDARY F X18 2-WIRES	XFORMER COIL	0.250" SPADE LUG	18 GA ORANGE	16"
1047	RAW A1 + FROM D001K TO C001.2 +	#10 RING TONGUE	#10 RING TONGUE	10 GA RED	8.5"
1048	RAW A2 + FROM D002K TO C001.2 +	#10 RING TONGUE	#10 RING TONGUE	10 GA RED	7"
1049	RAW A3 + FROM D003K TO C001.2 +	#10 RING TONGUE	#10 RING TONGUE	10 GA RED	8"
1050	RAW A1 - FROM D004A TO C001.2	#8 RING TONGUE	#10 RING TONGUE	10 GA BLACK	10.5"
1051	RAW A2 - FROM D005A TO C001.2	#8 RING TONGUE	#10 RING TONGUE	10 GA BLACK	9"
1052	RAW A3 - FROM D006A TO C001.2	#8 RING TONGUE	#10 RING TONGUE	10 GA BLACK	8.5"
1053	RAW B1 - FROM D010A TO C003.4	#8 RING TONGUE	#10 RING TONGUE	10 GA YELLOW	7.5"
1054	RAW B2 - FROM D011A TO C003.4	#8 RING TONGUE	#10 RING TONGUE	10 GA YELLOW	7.5"
1055	RAW B3 - FROM D012A TO C003.4	#8 RING TONGUE	#10 RING TONGUE	10 GA YELLOW	9"
1056	RAW B1 + FROM D007K TO C003.4 +	#10 RING TONGUE	#10 RING TONGUE	10 GA BLACK	9"
1057	RAW B2 + FROM D008K TO C003.4 +	#10 RING TONGUE	#10 RING TONGUE	10 GA BLACK	9"
1058	RAW B3 + FROM D009K TO C003.4 +	#10 RING TONGUE	#10 RING TONGUE	10 GA BLACK	10"
1059	RAW C + TO C005 +	0.250" SPADE LUG	#10 RING TONGUE	14 GA ORANGE	6"
1060	RAW C - TO C005	0.250" SPADE LUG	#10 RING TONGUE	14 GA BLACK	6"
1061	RAW D - TO C006	0.250" SPADE LUG	#10 RING TONGUE	14 GA BLUE	6"
1062	RAW D + TO C006 +	0.250" SPADE LUG	#10 RING TONGUE	14 GA BLACK	6"
1063	RAW E + TO C007 +	0.250" SPADE LUG	#10 RING TONGUE	14 GA WHITE	8"

**BLS WIRING LIST**

1064	RAW E - TO C007	0.250" SPADE LUG	#10 RING TONGUE	14 GA BLACK	8"
1065	RAW F - TO C008	0.250" SPADE LUG	#10 RING TONGUE	14 GA GREEN	8.5"
1066	RAW F + TO C008 +	0.250" SPADE LUG	#10 RING TONGUE	14 GA BLACK	8.5"
1067	RAW A INPUT FROM C001 + TO Q801R	#10 RING TONGUE	#6 RING TONGUE	10 GA RED	20"
1068	RAW A FROM Q800R TO Q801R	#6 RING TONGUE	#6 RING TONGUE	10 GA RED	3"
1069	RAW A INPUT FROM C002 + TO Q801L	#10 RING TONGUE	#6 RING TONGUE	10 GA RED	17"
1070	RAW A INPUT FROM Q800L TO Q801L	#6 RING TONGUE	#6 RING TONGUE	10 GA RED	3"
1071	RAW B INPUT FROM C003 TO Q803 R	#10 RING TONGUE	#6 RING TONGUE	10 GA YELLOW	15"
1072	RAW B INPUT FROM Q802R TO Q803R	#6 RING TONGUE	#6 RING TONGUE	10 GA YELLOW	3"
1073	RAW B INPUT FROM C004 TO Q803 L	#10 RING TONGUE	#6 RING TONGUE	10 GA YELLOW	22.5"
1074	RAW B INPUT FROM C802L TO Q803L	#6 RING TONGUE	#6 RING TONGUE	10 GA YELLOW	3"
1075	RAW C INPUT FROM C005 + TO Q804R	#10 RING TONGUE	#6 RING TONGUE	14 GA ORANGE	20"
1076	RAW C INPUT FROM C005 + TO Q804L	#10 RING TONGUE	#6 RING TONGUE	14 GA ORANGE	11.5"
1077	RAW D INPUT FROM C006 TO Q805R	#10 RING TONGUE	#6 RING TONGUE	14 GA BLUE	21"
1078	RAW D INPUT FROM C006 TO Q805L	#10 RING TONGUE	#6 RING TONGUE	14 GA BLUE	10"
1079	RAW E INPUT FROM C007 + TO Q806R	#10 RING TONGUE	#6 RING TONGUE	14 GA WHITE	26"
1080	RAW E INPUT FROM C007 + TO Q806L	#10 RING TONGUE	#6 RING TONGUE	14 GA WHITE	13"
1081	RAW F INPUT FROM C008 TO Q807R	#10 RING TONGUE	#6 RING TONGUE	14 GA GREEN	26"
1082	RAW F INPUT FROM C008 TO Q807L	#10 RING TONGUE	#6 RING TONGUE	14 GA GREEN	13"
1083	A OUT R FROM Q800R EMITTER TO R800R	SOLDER TO EMIT. SEE ASSEM 1	SOLDER TO RESISTOR	12 GA BUS WIRE	2"
1084	A OUT R FROM Q801R EMITTER TO R801R	SOLDER TO EMIT. SEE ASSEM 1	SOLDER TO RESISTOR	12 GA BUS WIRE	2"
1085	A OUT R FROM R800R TO R810R TO R801R	SOLDER TO RESIS. SEE ASSEM. 1	SOLDER TO RESISTOR	12 GA BUS WIRE	2"
1086	A OUT L FROM Q800L EMITTER TO R800L	SOLDER TO EMIT. SEE ASSEM 1	SOLDER TO RESISTOR	12 GA BUS WIRE	2"
1087	A OUT L FROM Q801L EMITTER TO R801L	SOLDER TO EMIT. SEE ASSEM 1	SOLDER TO RESISTOR	12 GA BUS WIRE	2"
1088	A OUT L FROM R800L TO R810L TO R801L	SOLDER TO RESIS. SEE ASSEM. 1	SOLDER TO RESISTOR	12 GA BUS WIRE	2"
1089	B OUT R FROM Q802R EMITTER TO R802R	SOLDER TO EMIT. SEE ASSEM 1	SOLDER TO RESISTOR	12 GA BUS WIRE	2"
1090	B OUT R FROM Q803R EMITTER TO R803R	SOLDER TO EMIT. SEE ASSEM 1	SOLDER TO RESISTOR	12 GA BUS WIRE	2"
1091	B OUT R FROM R802R TO R813R TO R803R	SOLDER TO RESIS. SEE ASSEM. 1	SOLDER TO RESISTOR	12 GA BUS WIRE	2"
1092	B OUT L FROM Q802L EMITTER TO R802L	SOLDER TO EMIT. SEE ASSEM 1	SOLDER TO RESISTOR	12 GA BUS WIRE	2"
1093	B OUT L FROM Q803L EMITTER TO R803L	SOLDER TO EMIT. SEE ASSEM 1	SOLDER TO RESISTOR	12 GA BUS WIRE	2"
1094	B OUT L FROM R802L TO R813L TO R803L	SOLDER TO RESIS. SEE ASSEM. 1	SOLDER TO RESISTOR	12 GA BUS WIRE	2"
1095	C OUT R FROM Q804R EMITTER TO R804R	SOLDER TO EMIT. SEE ASSEM 1	SOLDER TO RESISTOR	12 GA BUS WIRE	2"
1096	C OUT L FROM Q804L EMITTER TO R804L	SOLDER TO EMIT. SEE ASSEM 1	SOLDER TO RESISTOR	12 GA BUS WIRE	2"
1097	D OUT R FROM Q805R EMITTER TO R805R	SOLDER TO EMIT. SEE ASSEM 1	SOLDER TO RESISTOR	12 GA BUS WIRE	2"
1098	D OUT L FROM Q805L EMITTER TO R805L	SOLDER TO EMIT. SEE ASSEM 1	SOLDER TO RESISTOR	12 GA BUS WIRE	2"
1099	E OUT R FROM Q806R EMITTER TO R806R	SOLDER TO EMIT. SEE ASSEM 1	SOLDER TO RESISTOR	12 GA BUS WIRE	2"
1100	E OUT L FROM Q806L EMITTER TO R806L	SOLDER TO EMIT. SEE ASSEM 1	SOLDER TO RESISTOR	12 GA BUS WIRE	2"
1101	F OUT R FROM Q807R EMITTER TO R807R	SOLDER TO EMIT. SEE ASSEM 1	SOLDER TO RESISTOR	12 GA BUS WIRE	2"
1102	F OUT L FROM Q807L EMITTER TO R807L	SOLDER TO EMIT. SEE ASSEM 1	SOLDER TO RESISTOR	12 GA BUS WIRE	2"
1103	A OUT R FROM R810R TO C200.201R +	BUTT SPLICE/SOLDER SEE ASSM.1	#10 RING TONGUE	10 GA RED	19.5"

**BLS WIRING LIST**

1104 A OUT L FROM R810L TO C100,101L +	BUTT SPLICE/SOLDER SEE ASSM.1	#10 RING TONGUE	10 GA RED	13"
1105 B OUT R FROM R813R TO C202R	BUTT SPLICE/SOLDER SEE ASSM.1	#10 RING TONGUE	10 GA YELLOW	15"
1106 B OUT L FROM R813L TO C102L	BUTT SPLICE/SOLDER SEE ASSM.1	#10 RING TONGUE	10 GA YELLOW	12.5"
1107 C OUT R FROM R804R TO C203R +	SOLDER TO RESISTOR SEE ASSM.1	#10 RING TONGUE	14 GA ORANGE	16.5"
1108 C OUT L FROM R804L TO C103L +	SOLDER TO RESISTOR SEE ASSM.1	#10 RING TONGUE	14 GA ORANGE	19.5"
1109 D OUT R FROM R805R TO C204R	SOLDER TO RESISTOR SEE ASSM.1	#10 RING TONGUE	14 GA BLUE	11.5"
1110 D OUT L FROM R805L TO C104L	SOLDER TO RESISTOR SEE ASSM.1	#10 RING TONGUE	14 GA BLUE	14"
1111 E OUT R FROM R806R TO C205R +	SOLDER TO RESISTOR SEE ASSM.1	#10 RING TONGUE	14 GA WHITE	19"
1112 E OUT L FROM R806L TO C105L +	SOLDER TO RESISTOR SEE ASSM.1	#10 RING TONGUE	14 GA WHITE	18"
1113 F OUT R FROM R807R TO C206R	SOLDER TO RESISTOR SEE ASSM.1	#10 RING TONGUE	14 GA GREEN	15"
1114 F OUT L FROM R807L TO C106L	SOLDER TO RESISTOR SEE ASSM.1	#10 RING TONGUE	14 GA GREEN	16"
1115 A OUT R FROM C200,201R + TO PANEL	#10 RING TONGUE	75 SERIES CRIMP SEE ASSEM. 2	10 GA RED	12"
1116 A OUTR +VSENS FROM REG TO PANEL	8 PIN 0.1" MOLEX HYBPR PIN 2	SAME END 2 ABOVE SEE ASSEM.2	28 GA RED	25"
1117 A OUT L FROM C100,101L + TO PANEL	#10 RING TONGUE	75 SERIES CRIMP SEE ASSEM. 2	10 GA RED	11"
1118 A OUTL +VSENS FROM REG TO PANEL	8 PIN 0.1" MOLEX HYBPL PIN 2	SAME END 2 ABOVE SEE ASSEM. 2	28 GA RED	25"
1119 A OUTR COM FROM C200,201R TO PANEL	#10 RING TONGUE	75 SERIES CRIMP SEE ASSEM. 2	10 GA BLACK	12"
1120 A OUTR -VSENS FROM REG TO PANEL	8 PIN 0.1" MOLEX HYBPR PIN 3	SAME END 2 ABOVE SEE ASSEM. 2	28 GA BLACK	25"
1121 A OUTL COM FROM C100,101L TO PANEL	#10 RING TONGUE	75 SERIES CRIMP SEE ASSEM. 2	10 GA BLACK	11"
1122 A OUTL -VSENS FROM REG TO PANEL	8 PIN 0.1" MOLEX HYBPL PIN 3	SAME END 2 ABOVE SEE ASSEM. 2	28 GA BLACK	25"
1123 B OUT R FROM C202R TO PANEL	#10 RING TONGUE	75 SERIES CRIMP SEE ASSEM. 2	10 GA YELLOW	10"
1124 B OUTR -VSENS FROM REG TO PANEL	8 PIN 0.1" MOLEX HYBPR PIN 5	SAME END 2 ABOVE SEE ASSEM. 2	28 GA YELLOW	25"
1125 B OUT L FROM C102L TO PANEL	#10 RING TONGUE	75 SERIES CRIMP SEE ASSEM. 2	10 GA YELLOW	11"
1126 B OUTL -VSENS FROM REG TO PANEL	8 PIN 0.1" MOLEX HYBPL PIN 5	SAME END 2 ABOVE SEE ASSEM. 2	28 GA YELLOW	25"
1127 B OUTR COM FROM C202R + TO PANEL	#10 RING TONGUE	75 SERIES CRIMP SEE ASSEM. 2	10 GA BLACK	10"
1128 B OUTR +VSENS FROM REG TO PANEL	8 PIN 0.1" MOLEX HYBPR PIN 6	SAME END 2 ABOVE SEE ASSEM. 2	28 GA BLACK	25"
1129 B OUTL COM FROM C102L + TO PANEL	#10 RING TONGUE	75 SERIES CRIMP SEE ASSEM. 2	10 GA BLACK	10"
1130 B OUTRL+VSENS FROM REG TO PANEL	8 PIN 0.1" MOLEX HYBPL PIN 6	SAME END 2 ABOVE SEE ASSEM. 2	28 GA BLACK	25"
1131 C OUT R FROM C203R + TO PANEL	#10 RING TONGUE	AMODE CRIMP CONN SEE ASSEM. 2	14 GA ORANGE	11"
1132 C OUTR +VSENS FROM REG TO PANEL	8 PIN 0.1" MOLEX DRVPR PIN 2	SAME END 2 ABOVE SEE ASSEM. 2	28 GA ORANGE	25"
1133 C OUT L FROM C103L + TO PANEL	#10 RING TONGUE	AMODE CRIMP CONN SEE ASSEM. 2	14 GA ORANGE	8.5"
1134 C OUTL +VSENS FROM REG TO PANEL	8 PIN 0.1" MOLEX DRVPL PIN 2	SAME END 2 ABOVE SEE ASSEM. 2	28 GA ORANGE	25"
1135 C OUTR COM FROM C203R TO PANEL	#10 RING TONGUE	AMODE CRIMP CONN SEE ASSEM. 2	14 GA BLACK	11"
1136 C OUTR -VSENS FROM REG TO PANEL	8 PIN 0.1" MOLEX DRVPR PIN 3	SAME END 2 ABOVE SEE ASSEM. 2	28 GA BLACK	25"
1137 C OUTL COM FROM C103L TO PANEL	#10 RING TONGUE	AMODE CRIMP CONN SEE ASSEM. 2	14 GA BLACK	8"
1138 C OUTL -VSENS FROM REG TO PANEL	8 PIN 0.1" MOLEX DRVPL PIN 3	SAME END 2 ABOVE SEE ASSEM. 2	28 GA BLACK	25"
1139 D OUT R FROM C204R TO PANEL	#10 RING TONGUE	AMODE CRIMP CONN SEE ASSEM. 2	14 GA BLUE	12.5"
1140 D OUTR -VSENS FROM REG TO PANEL	8 PIN 0.1" MOLEX DRVPR PIN 5	SAME END 2 ABOVE SEE ASSEM. 2	28 GA BLUE	25"
1141 D OUT L FROM C104L TO PANEL	#10 RING TONGUE	AMODE CRIMP CONN SEE ASSEM. 2	14 GA BLUE	9.5"
1142 D OUTL -VSENS FROM REG TO PANEL	8 PIN 0.1" MOLEX DRVPL PIN 5	SAME END 2 ABOVE SEE ASSEM. 2	28 GA BLUE	25"
1143 D OUTR COM FROM C204R + TO PANEL	#10 RING TONGUE	AMODE CRIMP CONN SEE ASSEM. 2	14 GA BLACK	11.5"

**BLS WIRING LIST**

1144	D OUTR +VSENS FROM REG TO PANEL	8 PIN 0.1" MOLEX DRVPR PIN 6	SAME END 2 ABOVE SEE ASSEM. 2	28 GA BLACK	25"
1145	D OUTL COM FROM C104L + TO PANEL	#10 RING TONGUE	AMODE CRIMP CONN SEE ASSEM. 2	14 GA BLACK	9"
1146	D OUTL +VSENS FROM REG TO PANEL	8 PIN 0.1" MOLEX DRVPL PIN 6	SAME END 2 ABOVE SEE ASSEM. 2	28 GA BLACK	25"
1147	E OUT R FROM C205R + TO PANEL	#10 RING TONGUE	AMODE CRIMP CONN SEE ASSEM. 2	14 GA WHITE	11"
1148	E OUTR +VSENS FROM REG TO PANEL	8 PIN 0.1" MOLEX LOGPR PIN 2	SAME END 2 ABOVE SEE ASSEM. 2	28 GA WHITE	25"
1149	E OUT L FROM C105L + TO PANEL	#10 RING TONGUE	AMODE CRIMP CONN SEE ASSEM. 2	14 GA WHITE	10"
1150	E OUTL +VSENS FROM REG TO PANEL	8 PIN 0.1" MOLEX LOGPL PIN 2	SAME END 2 ABOVE SEE ASSEM. 2	28 GA WHITE	25"
1151	E OUTR COM FROM C205R TO PANEL	#10 RING TONGUE	AMODE CRIMP CONN SEE ASSEM. 2	14 GA BLACK	10"
1152	E OUTR -VSENS FROM REG TO PANEL	8 PIN 0.1" MOLEX LOGPR PIN 3	SAME END 2 ABOVE SEE ASSEM. 2	28 GA BLACK	25"
1153	E OUTL COM FROM C105L TO PANEL	#10 RING TONGUE	AMODE CRIMP CONN SEE ASSEM. 2	14 GA BLACK	9.5"
1154	E OUTL -VSENS FROM REG TO PANEL	8 PIN 0.1" MOLEX LOGPL PIN 3	SAME END 2 ABOVE SEE ASSEM. 2	28 GA BLACK	25"
1155	F OUT R FROM C206R TO PANEL	#10 RING TONGUE	AMODE CRIMP CONN SEE ASSEM. 2	14 GA GREEN	13"
1156	F OUTR -VSENS FROM REG TO PANEL	8 PIN 0.1" MOLEX LOGPR PIN 5	SAME END 2 ABOVE SEE ASSEM. 2	28 GA GREEN	25"
1157	F OUT L FROM C106L TO PANEL	#10 RING TONGUE	AMODE CRIMP CONN SEE ASSEM. 2	14 GA GREEN	10"
1158	F OUTL -VSENS FROM REG TO PANEL	8 PIN 0.1" MOLEX LOGPL PIN 5	SAME END 2 ABOVE SEE ASSEM. 2	28 GA GREEN	25"
1159	F OUTR COM FROM C206R + TO PANEL	#10 RING TONGUE	AMODE CRIMP CONN SEE ASSEM. 2	14 GA BLACK	12"
1160	F OUTR +VSENS FROM REG TO PANEL	8 PIN 0.1" MOLEX LOGPR PIN 6	SAME END 2 ABOVE SEE ASSEM. 2	28 GA BLACK	25"
1161	F OUTL COM FROM C106L + TO PANEL	#10 RING TONGUE	AMODE CRIMP CONN SEE ASSEM. 2	14 GA BLACK	9"
1162	F OUTL +VSENS FROM REG TO PANEL	8 PIN 0.1" MOLEX LOGPL PIN 6	SAME END 2 ABOVE SEE ASSEM. 2	28 GA BLACK	25"
1163	AUX +5 R FROM C205+ TO PANEL	#10 RING TONGUE	AMODE CRIMP CONN SEE ASSEM. 2	14 GA WHITE	14"
1164	AUX +5 COM R FROM C205 TO PANEL	#10 RING TONGUE	AMODE CRIMP CONN SEE ASSEM. 2	14 GA BLACK	14"
1165	AUX -5.2 R FROM C206- TO PANEL	#10 RING TONGUE	AMODE CRIMP CONN SEE ASSEM. 2	14 GA GREEN	17"
1166	AUX -5.2 COM R FROM C206+ TO PANEL	#10 RING TONGUE	AMODE CRIMP CONN SEE ASSEM. 2	14 GA BLACK	17"
1167	A OUTR +IMON FROM R810R TO REGULATOR	SOLDER TO QSIDE OF R810R	3 PIN 0.1" MOLEX PIN 1	28 GA RED	13"
1168	A OUTR -IMON FROM R810R TO REGULATOR	SOLDER TO CSIDE OF R810R	3 PIN 0.1" MOLEX PIN 3	28 GA BLACK	13"
1169	A OUTL +IMON FROM R810L TO REGULATOR	SOLDER TO QSIDE OF R810L	3 PIN 0.1" MOLEX PIN 1	28 GA RED	21"
1170	A OUTL -IMON FROM R810L TO REGULATOR	SOLDER TO CSIDE OF R810L	3 PIN 0.1" MOLEX PIN 3	28 GA BLACK	21"
1171	B OUTR -IMON FROM R813R TO REGULATOR	SOLDER TO QSIDE OF R813R	3 PIN 0.1" MOLEX PIN 1	28 GA YELLOW	17"
1172	B OUTR +IMON FROM R813R TO REGULATOR	SOLDER TO CSIDE OF R813R	3 PIN 0.1" MOLEX PIN 3	28 GA BLACK	17"
1173	B OUTL -IMON FROM R813L TO REGULATOR	SOLDER TO QSIDE OF R813L	3 PIN 0.1" MOLEX PIN 1	28 GA YELLOW	19"
1174	B OUTL +IMON FROM R813L TO REGULATOR	SOLDER TO CSIDE OF R813L	3 PIN 0.1" MOLEX PIN 3	28 GA BLACK	19"
1175	C OUTR +IMON FROM R804R TO REGULATOR	SOLDER TO QSIDE OF R804R	3 PIN 0.1" MOLEX PIN 1	28 GA ORANGE	17"
1176	C OUTR -IMON FROM R804R TO REGULATOR	SOLDER TO CSIDE OF R804R	3 PIN 0.1" MOLEX PIN 3	28 GA BLACK	17"
1177	C OUTL +IMON FROM R804L TO REGULATOR	SOLDER TO QSIDE OF R804L	3 PIN 0.1" MOLEX PIN 1	28 GA ORANGE	16"
1178	C OUTL -IMON FROM R804L TO REGULATOR	SOLDER TO CSIDE OF R804L	3 PIN 0.1" MOLEX PIN 3	28 GA BLACK	16"
1179	D OUTR -IMON FROM R805R TO REGULATOR	SOLDER TO QSIDE OF R805R	3 PIN 0.1" MOLEX PIN 1	28 GA BLUE	19"
1180	D OUTR +IMON FROM R805R TO REGULATOR	SOLDER TO CSIDE OF R805R	3 PIN 0.1" MOLEX PIN 3	28 GA BLACK	19"
1181	D OUTL -IMON FROM R805L TO REGULATOR	SOLDER TO QSIDE OF R805L	3 PIN 0.1" MOLEX PIN 1	28 GA BLUE	15"
1182	D OUTL +IMON FROM R805L TO REGULATOR	SOLDER TO CSIDE OF R805L	3 PIN 0.1" MOLEX PIN 3	28 GA BLACK	15"
1183	E OUTR +IMON FROM R806R TO REGULATOR	SOLDER TO QSIDE OF R806R	3 PIN 0.1" MOLEX PIN 1	28 GA WHITE	20"

## BLS WIRING LIST

1184	E OUTR -IMON FROM R806R TO REGULATOR	SOLDER TO CSIDE OF R806R	3 PIN 0.1" MOLEX PIN 3	28 GA BLACK	20"
1185	E OUTL +IMON FROM R806L TO REGULATOR	SOLDER TO QSIDE OF R806L	3 PIN 0.1" MOLEX PIN 1	28 GA WHITE	13"
1186	E OUTL -IMON FROM R806L TO REGULATOR	SOLDER TO CSIDE OF R806L	3 PIN 0.1" MOLEX PIN 3	28 GA BLACK	13"
1187	F OUTR -IMON FROM R807R TO REGULATOR	SOLDER TO QSIDE OF R807R	3 PIN 0.1" MOLEX PIN 1	28 GA GREEN	22"
1188	F OUTR +IMON FROM R807R TO REGULATOR	SOLDER TO CSIDE OF R807R	3 PIN 0.1" MOLEX PIN 3	28 GA BLACK	22"
1189	F OUTL -IMON FROM R807L TO REGULATOR	SOLDER TO QSIDE OF R807L	3 PIN 0.1" MOLEX PIN 1	28 GA GREEN	13"
1190	F OUTL +IMON FROM R807L TO REGULATOR	SOLDER TO CSIDE OF R807L	3 PIN 0.1" MOLEX PIN 3	28 GA BLACK	13"
1191	A OUTR TMPR0 FROM Q800R TO FAULT	SOLDER TO LM35 3 WIRE ASSEM	3 PIN 0.100" MOLEX. SEE ASSM.3	28 GA OR,WH,BL	13"
1192	A OUTL TMPL0 FROM Q800L TO FAULT	SOLDER TO LM35 3 WIRE ASSEM	3 PIN 0.100" MOLEX. SEE ASSM.3	28 GA OR,WH,BL	18"
1193	B OUTR TMPR1 FROM Q802R TO FAULT	SOLDER TO LM35 3 WIRE ASSEM	3 PIN 0.100" MOLEX. SEE ASSM.3	28 GA OR,WH,BL	17"
1194	B OUTL TMPL1 FROM Q802L TO FAULT	SOLDER TO LM35 3 WIRE ASSEM	3 PIN 0.100" MOLEX. SEE ASSM.3	28 GA OR,WH,BL	20"
1195	C OUTR TMPR2 FROM Q804R TO FAULT	SOLDER TO LM35 3 WIRE ASSEM	3 PIN 0.100" MOLEX. SEE ASSM.3	28 GA OR,WH,BL	16"
1196	C OUTL TMPL2 FROM Q804L TO FAULT	SOLDER TO LM35 3 WIRE ASSEM	3 PIN 0.100" MOLEX. SEE ASSM.3	28 GA OR,WH,BL	17"
1197	D OUTR TMPR3 FROM Q805R TO FAULT	SOLDER TO LM35 3 WIRE ASSEM	3 PIN 0.100" MOLEX. SEE ASSM.3	28 GA OR,WH,BL	20"
1198	D OUTL TMPL3 FROM Q805L TO FAULT	SOLDER TO LM35 3 WIRE ASSEM	3 PIN 0.100" MOLEX. SEE ASSM.3	28 GA OR,WH,BL	18"
1199	E OUTR TMPR4 FROM Q806R TO FAULT	SOLDER TO LM35 3 WIRE ASSEM	3 PIN 0.100" MOLEX. SEE ASSM.3	28 GA OR,WH,BL	21"
1200	E OUTL TMPL4 FROM Q806L TO FAULT	SOLDER TO LM35 3 WIRE ASSEM	3 PIN 0.100" MOLEX. SEE ASSM.3	28 GA OR,WH,BL	20"
1201	F OUTR TMPR5 FROM Q807R TO FAULT	SOLDER TO LM35 3 WIRE ASSEM	3 PIN 0.100" MOLEX. SEE ASSM.3	28 GA OR,WH,BL	23"
1202	F OUTL TMPL5 FROM Q807L TO FAULT	SOLDER TO LM35 3 WIRE ASSEM	3 PIN 0.100" MOLEX. SEE ASSM.3	28 GA OR,WH,BL	20"
1203	A OUTR BASE DRIVE TO TERM STRIP AR	SOLDER TO TERM STRIP	8 PIN 0.1" MOLEX PIN 1 ASSEM 4	28 GA RED	17"
1204	A OUTR FROM TERM STRIP TO BASE Q800R	SOLDER TO BASE ASSEMBLY	SOLDER TO TERM STRIP	28 GA RED	7"
1205	A OUTR FROM TERM STRIP TO BASE Q801R	SOLDER TO BASE ASSEMBLY	SOLDER TO TERM STRIP	28 GA RED	6"
1206	A OUTL BASE DRIVE TO TERM STRIP AL	SOLDER TO TERM STRIP AL	8 PIN 0.1" MOLEX PIN 1 ASSEM 4	28 GA RED	18"
1207	A OUTL FROM TERM STRIP TO BASE Q800L	SOLDER TO BASE ASSEMBLY	SOLDER TO TERM STRIP	28 GA RED	4"
1208	A OUTL FROM TERM STRIP TO BASE Q801L	SOLDER TO BASE ASSEMBLY	SOLDER TO TERM STRIP	28 GA RED	4"
1209	B OUTR BASE DRIVE TO TERM STRIP BR	SOLDER TO TERM STRIP BR	8 PIN 0.1" MOLEX PIN 5 ASSEM 4	28 GA YELLOW	19"
1210	B OUTR FROM TERM STRIP TO BASE Q802R	SOLDER TO BASE ASSEMBLY	SOLDER TO TERM STRIP	28 GA YELLOW	6"
1211	B OUTR FROM TERM STRIP TO Q803R	SOLDER TO BASE ASSEMBLY	SOLDER TO TERM STRIP	28 GA YELLOW	6"
1212	B OUTL BASE DRIVE TO TERM STRIP BL	SOLDER TO TERM STRIP BL	8 PIN 0.1" MOLEX PIN 5 ASSEM 4	28 GA YELLOW	18"
1213	B OUTL FROM TERM STRIP TO BASE Q802L	SOLDER TO BASE ASSEMBLY	SOLDER TO TERM STRIP	28 GA YELLOW	7"
1214	B OUTL FROM TERM STRIP TO BASE Q803L	SOLDER TO BASE ASSEMBLY	SOLDER TO TERM STRIP	28 GA YELLOW	5"
1215	C OUTR BASE DRIVE	SOLDER TO BASE ASSEMBLY	8 PIN 0.1" MOLEX PIN 1 ASSEM 4	28 GA ORANGE	14"
1216	C OUTL BASE DRIVE	SOLDER TO BASE ASSEMBLY	8 PIN 0.1" MOLEX PIN 1 ASSEM 4	28 GA ORANGE	15"
1217	D OUTR BASE DRIVE	SOLDER TO BASE ASSEMBLY	8 PIN 0.1" MOLEX PIN 5 ASSEM 4	28 GA BLUE	18"
1218	D OUTL BASE DRIVE	SOLDER TO BASE ASSEMBLY	8 PIN 0.1" MOLEX PIN 5 ASSEM 4	28 GA BLUE	18"
1219	E OUTR BASE DRIVE	SOLDER TO BASE ASSEMBLY	8 PIN 0.1" MOLEX PIN 1 ASSEM 4	28 GA WHITE	18"
1220	E OUTL BASE DRIVE	SOLDER TO BASE ASSEMBLY	8 PIN 0.1" MOLEX PIN 1 ASSEM 4	28 GA WHITE	18"
1221	F OUTR BASE DRIVE	SOLDER TO BASE ASSEMBLY	8 PIN 0.1" MOLEX PIN 5 ASSEM 4	28 GA GREEN	19"
1222	F OUTL BASE DRIVE	SOLDER TO BASE ASSEMBLY	8 PIN 0.1" MOLEX PIN 5 ASSEM 4	28 GA GREEN	18"
1223	RAW A AC JUMPER FROM D004K TO D001A	#8 RING TONGUE	#10 RING TONGUE	3/8" BRAID	3.5"

**BLS WIRING LIST**

1224	RAW A AC JUMPER FROM D004K TO D001A	#8 RING TONGUE	#10 RING TONGUE	3/8" BRAID	3.5"
1225	RAW A AC JUMPER FROM D005K TO D002A	#8 RING TONGUE	#10 RING TONGUE	3/8" BRAID	3.5"
1226	RAW A AC JUMPER FROM D005K TO D002A	#8 RING TONGUE	#10 RING TONGUE	3/8" BRAID	3.5"
1227	RAW A AC JUMPER FROM D006K TO D003A	#8 RING TONGUE	#10 RING TONGUE	3/8" BRAID	3.5"
1228	RAW A AC JUMPER FROM D006K TO D003A	#8 RING TONGUE	#10 RING TONGUE	3/8" BRAID	3.5"
1229	RAW B AC JUMPER FROM D010K TO D007A	#8 RING TONGUE	#10 RING TONGUE	3/8" BRAID	3.5"
1230	RAW B AC JUMPER FROM D010K TO D007A	#8 RING TONGUE	#10 RING TONGUE	3/8" BRAID	3.5"
1231	RAW B AC JUMPER FROM D011K TO D008A	#8 RING TONGUE	#10 RING TONGUE	3/8" BRAID	3.5"
1232	RAW B AC JUMPER FROM D011K TO D008A	#8 RING TONGUE	#10 RING TONGUE	3/8" BRAID	3.5"
1233	RAW B AC JUMPER FROM D012K TO D009A	#8 RING TONGUE	#10 RING TONGUE	3/8" BRAID	3.5"
1234	RAW B AC JUMPER FROM D012K TO D009A	#8 RING TONGUE	#10 RING TONGUE	3/8" BRAID	3.5"
1235	LOC/REM SW TO LOGIC PIN 1 +5 TO RON UP	SOLDER TO SWITCH SEE ASSEM 5	8 PIN 0.1" MOLEX PIN 1	28 GA BROWN	22"
1236	LOC/REM SW R/L 2 UP TO LON UP	SOLDER TO SWITCH SEE ASSEM 5	SOLDER TO SWITCH	28 GA BROWN	1"
1237	LOC/REM SW R/L 2 UP TO RON UP	SOLDER TO SWITCH SEE ASSEM 5	SOLDER TO SWITCH	28 GA BROWN	1"
1238	LOC/REM SW TO LOGIC PIN 8 GND TO R/L 2 DOWN	SOLDER TO SWITCH SEE ASSEM 5	8 PIN 0.1" MOLEX PIN 8	28 GA GREY	22"
1239	LOC/REM SW R/L 2 DOWN TO LON DOWN	SOLDER TO SWITCH SEE ASSEM 5	SOLDER TO SWITCH	28 GA GREY	1"
1240	LOC/REM SW R/L 2 DOWN TO RON DOWN	SOLDER TO SWITCH SEE ASSEM 5	SOLDER TO SWITCH	28 GA GREY	1"
1241	LOC/REM SW R/L 1 DOWN TO L ON/OFF C	SOLDER TO SWITCH SEE ASSEM 5	SOLDER TO SWITCH	28 GA WHITE	1"
1242	LOC/REM SW R/L 3 DOWN TO R ON/OFF C	SOLDER TO SWITCH SEE ASSEM 5	SOLDER TO SWITCH	28 GA WHITE	1"
1243	LOC/REM SW TO LOGIC PIN 2 TO R/L C2	SOLDER TO SWITCH SEE ASSEM 5	8 PIN 0.1" MOLEX PIN 2	28 GA RED	22"
1244	LOC/REM TO LOGIC PIN 3 TO R/L 1 UP	SOLDER TO SWITCH SEE ASSEM 5	8 PIN 0.1" MOLEX PIN 3	28 GA ORANGE	22"
1245	LOC/REM TO LOGIC PIN 4 TO R/L C1	SOLDER TO SWITCH SEE ASSEM 5	8 PIN 0.1" MOLEX PIN 4	28 GA YELLOW	22"
1246	LOC/REM TO LOGIC PIN 5 TO R/L 3 UP	SOLDER TO SWITCH SEE ASSEM 5	8 PIN 0.1" MOLEX PIN 5	28 GA GREEN	22"
1247	LOC/REM TO LOGIC PIN 6 TO R/L C3	SOLDER TO SWITCH SEE ASSEM 5	8 PIN 0.1" MOLEX PIN 6	28 GA BLUE	22"
1248	LOC/REM TO LOGIC PIN 7 TO RESET SW UP	SOLDER TO SWITCH SEE ASSEM 5	8 PIN 0.1" MOLEX PIN 7	28 GA VIOLET	22"
1249	LOC/REM SW RON DOWN TO RESET SW DOWN	SOLDER TO SWITCH SEE ASSEM 5	SOLDER TO SWITCH	28 GA GREY	2"
1250	REG PWR L FROM CNTLPWR TO LEFT REG PIN 1	6 PIN 0.156" MOLEX	6 PIN 0.156" MOLEX	22 GA VIOLET	28"
1251	REG PWR L FROM CNTLPWR TO LEFT REG PIN 2	6 PIN 0.156" MOLEX	6 PIN 0.156" MOLEX	22 GA BLACK	28"
1252	REG PWR L FROM CNTLPWR TO LEFT REG PIN 3	6 PIN 0.156" MOLEX	6 PIN 0.156" MOLEX	22 GA YELLOW	28"
1253	REG PWR L FROM CNTLPWR TO LEFT REG PIN 4	6 PIN 0.156" MOLEX	6 PIN 0.156" MOLEX	22 GA ORANGE	28"
1254	REG PWR L FROM CNTLPWR TO LEFT REG PIN 5	6 PIN 0.156" MOLEX	6 PIN 0.156" MOLEX	22 GA BLK	28"
1255	REG PWR L FROM CNTLPWR TO LEFT REG PIN 6	6 PIN 0.156" MOLEX	6 PIN 0.156" MOLEX	22 GA BLUE	28"
1256	REG PWR R FROM CNTLPWR TO RIGHT REG PIN 1	6 PIN 0.156" MOLEX	6 PIN 0.156" MOLEX	22 GA VIOLET	21"
1257	REG PWR R FROM CNTLPWR TO RIGHT REG PIN 2	6 PIN 0.156" MOLEX	6 PIN 0.156" MOLEX	22 GA BLACK	21"
1258	REG PWR R FROM CNTLPWR TO RIGHT REG PIN 3	6 PIN 0.156" MOLEX	6 PIN 0.156" MOLEX	22 GA YELLOW	21"
1259	REG PWR R FROM CNTLPWR TO RIGHT REG PIN 4	6 PIN 0.156" MOLEX	6 PIN 0.156" MOLEX	22 GA ORANGE	21"
1260	REG PWR R FROM CNTLPWR TO RIGHT REG PIN 5	6 PIN 0.156" MOLEX	6 PIN 0.156" MOLEX	22 GA BLK	21"
1261	REG PWR R FROM CNTLPWR TO RIGHT REG PIN 6	6 PIN 0.156" MOLEX	6 PIN 0.156" MOLEX	22 GA BLUE	21"
1262	FLT PWR L FROM CNTLPWR TO LEFT FAULT PIN 1	3 PIN 0.156" MOLEX	3 PIN 0.156" MOLEX	22 GA VIOLET	25"
1263	FLT PWR L FROM CNTLPWR TO LEFT FAULT PIN 2	3 PIN 0.156" MOLEX	3 PIN 0.156" MOLEX	22 GA BLACK	25"

**BLS WIRING LIST**

1264	FLT PWR L FROM CNTLPWR TO LEFT FAULT PIN 3	3 PIN 0.156" MOLEX	3 PIN 0.156" MOLEX	22 GA YELLOW	25"
1265	FLT PWR R FROM CNTLPWR TO RIGHT FAULT PIN 1	3 PIN 0.156" MOLEX	3 PIN 0.156" MOLEX	22 GA VIOLET	17"
1266	FLT PWR R FROM CNTLPWR TO RIGHT FAULT PIN 2	3 PIN 0.156" MOLEX	3 PIN 0.156" MOLEX	22 GA BLACK	17"
1267	FLT PWR R FROM CNTLPWR TO RIGHT FAULT PIN 3	3 PIN 0.156" MOLEX	3 PIN 0.156" MOLEX	22 GA YELLOW	17"
1268	LOG PWR FROM CNTLPWR TO LOGIC BD PIN 1	3 PIN 0.156" MOLEX	3 PIN 0.156" MOLEX	22 GA BLACK	18"
1269	LOG PWR FROM CNTLPWR TO LOGIC BD PIN 2	3 PIN 0.156" MOLEX	3 PIN 0.156" MOLEX	22 GA RED	18"
1270	LOG PWR FROM CNTLPWR TO LOGIC BD PIN 3	3 PIN 0.156" MOLEX	3 PIN 0.156" MOLEX	22 GA BLACK	18"
1271	R OVERTEMP + TO LOGIC BD	SPADE LUG 0.250"	SPADE LUG 0.186"	22 GA ORANGE	20"
1272	R OVERTEMP - TO LOGIC BD	SPADE LUG 0.250"	SPADE LUG 0.186"	22 GA BLACK	18"
1273	L OVER TEMP + TO LOGIC BD	SPADE LUG 0.250"	SPADE LUG 0.186"	22 GA YELLOW	14"
1274	L OVERTEMP - TO LOGIC BD	SPADE LUG 0.250"	SPADE LUG 0.186"	22 GA BLACK	12"
1275	DISPLAY BD TO CNTLPWR RIBBON CABLE	34 PIN FLAT CABLE CONN	34 PIN CABLE CONN	34 COND RIBBON	18"
1276	CNTLPWR BD TO LOGIC BD	40 PIN FLAT CABLE CONN	40 PIN CABLE CONN	40 COND RIBBON	20"
1277	LOGIC BD TO LEFT FAULT BD	40 PIN FLAT CABLE CONN	40 PIN CABLE CONN	40 COND RIBBON	8.5"
1278	LOGIC BD TO RIGHT FAULT BD	40 PIN FLAT CABLE CONN	40 PIN CABLE CONN	40 COND RIBBON	6"
1279	LEFT FAULT BD TO LEFT REGULATOR BD	34 PIN FLAT CABLE CONN	34 PIN CABLE CONN	34 COND RIBBON	9"
1280	RIGHT FAULT BD TO RIGHT REGULATOR BD	34 PIN FLAT CABLE CONN	34 PIN CABLE CONN	34 COND RIBBON	11"
1281	'A' C001,2- to C200,201 L-	#10 RING TONGUE	#10 RING TONGUE	10 GA BLACK	7"
1282	'A' C001,2- to C200,201 R-	#10 RING TONGUE	#10 RING TONGUE	10 GA BLACK	7"
1283	'B' C003,4+ to C202 L+	#10 RING TONGUE	#10 RING TONGUE	10 GA BLACK	7.5"
1284	'B' C003,4+ to C202 R+	#10 RING TONGUE	#10 RING TONGUE	10 GA BLACK	4.5"
1285	'C' C005- to C203 L-	#10 RING TONGUE	#10 RING TONGUE	14 GA BLACK	7.5"
1286	'C' C203L- to C203 R-	#10 RING TONGUE	#10 RING TONGUE	14 GA BLACK	4"
1287	'D' C204R+ to C204 L+	#10 RING TONGUE	#10 RING TONGUE	14 GA BLACK	4.5"
1288	'D' C006+ to C204 R+	#10 RING TONGUE	#10 RING TONGUE	14 GA BLACK	11.5"
1289	'E' C007- to C205 L-	#10 RING TONGUE	#10 RING TONGUE	14 GA BLACK	6"
1290	'E' C007- to C205 R-	#10 RING TONGUE	#10 RING TONGUE	14 GA BLACK	12.5"
1291	'F' C008+ to C206 L+	#10 RING TONGUE	#10 RING TONGUE	14 GA BLACK	5"
1292	'F' C008+ to C206 R+	#10 RING TONGUE	#10 RING TONGUE	14 GA BLACK	15"